Installing the printer in macOS operating system

EXTERNAL

Business Intelligence Business Link

Date	Version	Action	Author/Responsible
2025-02-12	1.0	Created	Jakub Płokita

Contents

Introduction	2
Driver download	2
Installation	4
Adding a printer	6
Printing test - authorization	10



Introduction

The instructions are designed to guide you step-by-step through the process of installing a printer available on business.link space in a macOS environment.

Driver download

Search for bizhub C451i driver available on manufacturer's website.

https://www.konicaminolta.co.uk/en-gb/customer-support/download-centre

Download the latest drivers, device	manuals and software for your Konica Minolta
Search your product:	Or make choice step by step:
bizhub C451i	A3 Multifunctional Colour
	bizhub C451i 🗸

Expand the **Drivers** list by clicking on the + icon or on **Click to open**.

Download the latest drivers, manuals an	d software for your Koni	ca Minolta device
Search your product:	Or make choice step by step:	
bizhub C451i	A3 Multifunctional Colour	~
	bizhub C451i	~
G0 →		
⊕ Drivers		Click to open

Set the filter for the version of your macOS software and then click on the icon to download the latest version of the available driver.

Drivers	OS Vortura 13 Version V			Click to
Printer Driver	Version			
Version	Release Date	Emulation	Description	Download
5.2.13A	Sep 27, 2024	PostScript	1	>

In the next step, accept the license agreement so that the .dmg file can be downloaded.



Installation

Unzip the downloaded driver and go through the next screens of the installer.



The installer will ask you to authorize the installation via Touch ID or user login and password.

 Introduction Read Me License Destination Select Installation Type Installation 	Installer Installer Installer is trying to install new software. Touch ID or enter your password to allow this. Use Password Cancel	A computer. Ilation of this software
KONICA MINOLTA	Customize	Go Back Install

Adding a printer

Ć.	Finder	File	Edit	View	Go	Window	He

To add a new printer, open **System Settings** by selecting the Apple icon.

About This Mac			
		_	
System Settings	2 updates		
App Store	2 updates		
Recent Items		>	
Force Quit Finder	光公元		
Sleep			
Restart			
Shut Down			

In the system settings, select Printers & Scanners and then Add Printer, Scanner or Fax...

A assertion	Default printer	Last Printer Used
Notifications	Default paper size	A4 (
3 Sound		
S Focus	Printers	
🔀 Screen Time	Canon G3010 series	
🕑 General	HP DeskJet 3630 series	
Appearance	• Offine	
O Accessibility	Ad	d Printer, Scanner, or Fax
Control Center		
🧕 Siri & Spotlight		
🕛 Privacy & Security		
E Desktop & Dock		
🚼 Displays		
🔝 Wallpaper		
Screen Saver		
Battery		
🚊 Lock Screen		
Touch ID & Password		
💴 Users & Groups		
Passwords		
🔯 Internet Accounts		
Game Center		
📟 Wallet & Apple Pay		
E Keyboard		

When a new window appears, select the **Advanced** tab.

If you don't have it, right-click on the top bar and select **Customize Toolbar...** then drag and drop the **Advanced** icon to the top bar.

lcon and Text			drag and
Text Only	e items into the toolbar		drop
Customize Toolbar		ē	ere
	s IP	Default	Advanced
	Flexible Space		

In the window that opens, select Type: Internet Printing Protocol (ipps)

• • •			Add Pri	inter	
	l.	Ĵ		ij	
Type Device URL	 Canon IJ Network Internet Printing Protocol Internet Printing Protocol (http) Internet Printing Protocol (https) Internet Printing Protocol (ipps) Jetdirect LPD/LPR Host or Printer Windows printer via spoolss 				

Then fill in the following data:

Devices: Another Devices

URL: ipps://10.140.22.10:8050/ipp/print

Name: enter your own printer name

In the **Use** line, select the software that was previously installed.

		Add F	Printer	
			8	00
Type	Internet Printing Protocol (ipps)			_
		 _		
Device:	Another Device			_
URL:	ipps://10.140.22.10:8050/ipp/print			
Name	your printer name			
Location				
Location Use				
Location Use				
Location Use	Choose a Driver Auto Select Generic PostScript Printer			
Location Use	Choose a Driver Auto Select Generic PostScript Printer Cossel PC Printer			

The stage is completed by selecting the value **Add**.

ting Protocol (ipps) ice 22.10:8050/ipp/print	_		•		®®	_	_		_		
ting Protocol (ipps) ice 22.10:8050/ipp/print	=			-	_	-	_	_	_	(
ting Protocol (ipps) ice 22.10:8050/ipp/print	_	=	-		=	-	_	=	_	(
ice 22.10:8050/ipp/print	_			-	_						
22.10:8050/ipp/print											20 C
name											
NOLTA C451i PS										(0
										Add	
er vil	er name MINOLTA C451i PS	er name VIINOLTA C451i PS	er name AINOLTA C451i PS	er name AINOLTA C451: PS	sr name MINOLTA C451: PS	er name MINOLTA C451i PS	er name MINOLTA C45% PS	er name MINOLTA C451i PS	er name MINOLTA C451i PS	er name MINOLTA C451: PS	er name MINOLTA C451: PS

The following printer configuration remains unchanged.

Setting up 'your printer's of can take full advantage of	er name' options are accurately shown here so you f them.
Paper Source Unit:	None
Finisher:	None
Punch Unit:	None
Z-Fold Unit:	None
Post Inserter:	None
Security Document Setting:	Do Not Release Secure Print ᅌ
	✓ Storage
	Secure Print Only
	Allow Public User
	Cancel

Printing test - authorization

Select the added printer and double-click on it, then select Printer Queue....

Click in the top bar on the **Printer** button then select **Print Test Page**

your printer name Edit	Printer ciobs Window Help	
	Pause	
	Make Default	жD
	Settings	жs
bez nazwy	Supply Levels	
	Print Test Page	
	Error Log	
	Printers & Scanners Preferences	εL

Since the printer does not yet have credentials saved (your login and password received from the BusinessLink front desk) the print job will be stopped - the message "Suspend for authentication". Click the button to renew the print job.

Enter the login and password provided by your local Customer Care team.

By default, your login used to log into the computer will be entered.

The printer has been installed and the test page sent to the printing system.

Walk up to any business.link printer, apply your access card, and then delete the test page print job - we don't want to charge you for this print.